



Cleaners

## FLUX REMOVER

### FLUX REMOVER AND DEGREASER

Flux Remover is a unique blend of solvents formulated to remove flux residues and uncured surface mount adhesives from printed circuit boards (PCB's). Flux Remover also effectively removes burnt-on flux residue, solder pastes and acrylic conformal coatings.

### PRODUCT CODES / FILL SIZES



30216 / 400ml

### APPLICATIONS

- Excellent removal of flux residues from PCB's and electronic components.
- Penetrates quickly and evaporates completely after use leaving a clean, dry surface.
- Removes uncured surface mount adhesive residues from stencils and application equipment.
- Removes acrylic conformal coatings.

### DIRECTIONS

- Not for use on live electrical equipment.
- Spray Ambersil Flux Remover liberally on to flux deposit, allow to run off and leave to dry.
- For heavy flux contamination, a second application may be required.
- Allow solvent to evaporate completely before operating the equipment.

## TECHNICAL DATA (WITHOUT PROPELLANT)

Appearance	Clear, colourless liquid
Odour	Sweet, characteristic
SG @ 25°C	0.66
Pressure @ 25°C	3.5 Bar
Discharge rate	1.1 g/sec
Initial boiling point	55°C
Flashpoint	Not applicable in sealed aerosol

## MATERIALS COMPATIBILITY

OK	-
CAUTION	May affect certain plastics. Always test a small, inconspicuous area before general use.
NOT OK	-

## STORAGE & SHELF LIFE

The product may be stored at normal ambient temperatures and has a shelf life of not less than 72 months with correct storage. Aerosols should always be stored below 50°C, away from direct heat and naked flame.

## HEALTH AND SAFETY

A separate Safety Data Sheet (SDS) according to EC Regulation 73/404/EEC and 648/2004/EC is available from Ambersil.com or via [info.uk@crcind.com](mailto:info.uk@crcind.com)

## MISREPRESENTATION ACT 1967

## TRADE DESCRIPTIONS ACT 1968

The information given in this publication is based on our experience and reports from customers. There are many factors outside our control and knowledge which affect the use and performance of our products and for which reason no warranty is given, express or implied. Users should make their own tests to determine the applicability of such information or the suitability of any products for their own particular purposes. Statements concerning the use of the products described herein are not to be construed as recommending the infringement of any patent and no liability for infringement arising out of any such use is to be assumed.

Version 2.0  
Created: July 2019  
Updated: N/A

CRC Industries UK Ltd.  
Wylds Road, Bridgwater  
Somerset, TA6 4DD  
United Kingdom

t +44 (0)1278 727200  
f +44 (0)1278 425644  
e [sales.uk@crcind.com](mailto:sales.uk@crcind.com)  
w [www.ambersil.com](http://www.ambersil.com)

Company Registered No. 04910479

VAT No. GB 821 5195 42

